


## ILLUMINATION

Connector No.	M35
Connector Name	COMBINATION SWITCH (SPIRAL CABLE)
Connector Type	TK06FY-EX-1V




Terminal No.	Color of Wire	Signal Name [Specification]
23	P	—

Connector No.	M36
Connector Name	COMBINATION SWITCH (SPIRAL CABLE)
Connector Type	TK08FGY-1V




Terminal No.	Color of Wire	Signal Name [Specification]
26	Y	—

Connector No.	M53
Connector Name	COMBINATION METER
Connector Type	SAB40FW



Terminal No.	Color of Wire	Signal Name [Specification]
1	V	BATTERY POWER SUPPLY
2	W	IGNITION POWER SUPPLY
3	B	GROUND
4	B	ILL. GND
5	B	GROUND
6	W	METER CONTROL SWITCH GROUND
21	L	CAN-H
22	P	CAN-L
23	LG	ILLUMINATION CONTROL SWITCH SIGNAL (-)
24	BR	ILLUMINATION CONTROL SWITCH SIGNAL (+)
40	V	ILLUMINATION CONTROL

Connector No.	M54
Connector Name	METER CONTROL SWITCH
Connector Type	TH12FW-NH




Terminal No.	Color of Wire	Signal Name [Specification]
1	BR	—
2	W	—
3	LG	—
4	R	—
5	V	—

Connector No.	M59
Connector Name	DIODE
Connector Type	24335 C9900




Terminal No.	Color of Wire	Signal Name [Specification]
1	V	—
2	P	—

Connector No.	M80
Connector Name	KEY SLOT
Connector Type	TH12FW-NH



Terminal No.	Color of Wire	Signal Name [Specification]
1	G	BAT
7	B	GND
11	R	KEY SWITCH SIGNAL

Connector No.	M72
Connector Name	MULTIFUNCTION SWITCH
Connector Type	TH16FW-NH



Terminal No.	Color of Wire	Signal Name [Specification]
4	P	ILL
5	P	ILL CONT

Connector No.	M73
Connector Name	SET-UP SWITCH
Connector Type	TK24FW-1V



Terminal No.	Color of Wire	Signal Name [Specification]
2	R	ILL+
4	V	ILL GND