


DOOR MIRROR

Connector No.	D1
Connector Name	WIRE TO WIRE
Connector Type	TH40FW-CS15




Terminal No.	Color of Wire	Signal Name [Specification]
44	L	-
45	Y	-
46	R	-
54	W	-
55	G	-

Connector No.	D3
Connector Name	DOOR MIRROR (DRIVER SIDE)
Connector Type	RH08MB



Terminal No.	Color of Wire	Signal Name [Specification]
2	Y	-
3	G	-
4	W	-
7	R	-
8	L	-

Connector No.	D31
Connector Name	WIRE TO WIRE
Connector Type	TH40FW-CS15




Terminal No.	Color of Wire	Signal Name [Specification]
44	L	-
45	Y	-
46	R	-
54	W	-
55	G	-

Connector No.	D33
Connector Name	DOOR MIRROR (PASSENGER SIDE)
Connector Type	RH08MB




Terminal No.	Color of Wire	Signal Name [Specification]
2	Y	-
3	G	-
4	W	-
7	R	-
8	L	-

Connector No.	M1
Connector Name	FUSE BLOCK (J/B)
Connector Type	NS06FW-M2




Terminal No.	Color of Wire	Signal Name [Specification]
5A	SB	-

Connector No.	M5
Connector Name	WIRE TO WIRE
Connector Type	TH40MW-CS15



Terminal No.	Color of Wire	Signal Name [Specification]
44	L	-
45	Y	-
46	O	-
54	W	-
55	G	-

Connector No.	M12
Connector Name	DOOR MIRROR REMOTE CONTROL SWITCH
Connector Type	NS12FW-CS



Terminal No.	Color of Wire	Signal Name [Specification]
1	B	- [With BOSE audio]
1	SB	- [Without BOSE audio]
2	Y	-
3	SB	-
4	G	-
5	W	-
6	G	-
7	W	-
8	O	-
9	L	-

Connector No.	M15
Connector Name	DIODE
Connector Type	ET02-2W



Terminal No.	Color of Wire	Signal Name [Specification]
1	SB	-
2	B	-