



ILLUMINATION

| | |
|----------------|-----------------|
| Connector No. | M80 |
| Connector Name | AV CONTROL UNIT |
| Connector Type | TH18FW-CS2 |



| Terminal No. | Color of Wire | Signal Name [Specification] |
|--------------|---------------|-----------------------------|
| 9 | R | ILLUMINATION |

| | |
|----------------|-----------------|
| Connector No. | M82 |
| Connector Name | AV CONTROL UNIT |
| Connector Type | TH12FW-NH |




| Terminal No. | Color of Wire | Signal Name [Specification] |
|--------------|---------------|-----------------------------|
| 70 | BR | COMM (CONT->DISP) |
| 71 | Y | COMM (DISP->CONT) |
| 72 | SHIELD | SHIELD |

| | |
|----------------|----------------|
| Connector No. | M102 |
| Connector Name | GLOVE BOX LAMP |
| Connector Type | A02FW |



| Terminal No. | Color of Wire | Signal Name [Specification] |
|--------------|---------------|-----------------------------|
| 1 | R | - |
| 2 | B | - |

| | |
|----------------|-----------------|
| Connector No. | M117 |
| Connector Name | WIRE TO WIRE |
| Connector Type | TH80MW-CS16-TM4 |




| Terminal No. | Color of Wire | Signal Name [Specification] |
|--------------|---------------|-----------------------------|
| 99 | V | - |

| | |
|----------------|---------------------------|
| Connector No. | M118 |
| Connector Name | BCM (BODY CONTROL MODULE) |
| Connector Type | M03FB-LC |




| Terminal No. | Color of Wire | Signal Name [Specification] |
|--------------|---------------|-----------------------------|
| 1 | GR | BAT (F/L) |

| | |
|----------------|---------------------------|
| Connector No. | M119 |
| Connector Name | BCM (BODY CONTROL MODULE) |
| Connector Type | NS16FW-CS |




| Terminal No. | Color of Wire | Signal Name [Specification] |
|--------------|---------------|-----------------------------|
| 11 | R | BAT (FUSE) |
| 13 | B | GND |

| | |
|----------------|---------------------------|
| Connector No. | M122 |
| Connector Name | BCM (BODY CONTROL MODULE) |
| Connector Type | TH40FB-NH |



| Terminal No. | Color of Wire | Signal Name [Specification] |
|--------------|---------------|-----------------------------|
| 87 | BR | COMBI SW INPUT 5 |
| 88 | V | COMBI SW INPUT 3 |
| 89 | BR | PUSH SW |
| 90 | P | CAN-L |
| 91 | L | CAN-H |
| 100 | W | PASSENGER DOOR REQUEST SW |
| 101 | V | DRIVER DOOR REQUEST SW |
| 107 | LG | COMBI SW INPUT 1 |
| 108 | R | COMBI SW INPUT 4 |
| 109 | Y | COMBI SW INPUT 2 |

| | |
|----------------|---------------------------|
| Connector No. | M123 |
| Connector Name | BCM (BODY CONTROL MODULE) |
| Connector Type | TH40FG-NH |



| Terminal No. | Color of Wire | Signal Name [Specification] |
|--------------|---------------|-----------------------------------|
| 121 | R | KEY SLOT SW |
| 133 | W | PUSH-BUTTON IGNITION SW ILL POWER |
| 142 | O | COMBI SW OUTPUT 5 |
| 143 | P | COMBI SW OUTPUT 1 |
| 144 | G | COMBI SW OUTPUT 2 |
| 145 | L | COMBI SW OUTPUT 3 |
| 146 | SB | COMBI SW OUTPUT 4 |
| 150 | GR | DRIVER DOOR SW |